

New JRC SAW FILTER

NSTS9116A

Application

GPS+GLONASS 1589.5MHz, BW=32MHz, Low Loss Type

Electrical Specification: (Table 1)

The device characteristics are measured in the circuit shown in Fig.1.

Item	Spec.	Typ.
Input and Output Impedance	-	50Ω
Nominal Center Frequency (f0)	-	1589.5MHz
Insertion Loss	2.0dB max.	1.35dB
Response Variation	1.0dB max.	0.3dB
Input and Output VSWR	2.0 max.	1.7
Out of Band Rejection (Relative to Through Level)	800 to 1000MHz	17dB min.
	1700 to 2100MHz	20dB min.

Operating Temperature: -40 to +105°C

Maximum Rating: (Table 2)

Table 2. Maximum Ratings

Item	Rating
Maximum Input Power (In Band)	+10dBm
Maximum DC Voltage	7.5V
Operating Temperature	-40 to +105°C
Storage Temperature	-40 to +110°C

Mechanical Specifications: (Fig.2)

Package is designed as small as 2.0x1.6x0.65[mm³] for SMD (Surface Mount Device) type.

Notice:

This part is electrostatic discharge sensitive and may be damaged by improper handling.

New Japan Radio Co., Ltd.

<https://www.njr.co.jp/products/device/index.html>

<https://www.njr.com/products/device/index.html>




Fig.1 Measuring circuit






Fig.2 Package dimensions (in mm)

Marking

- (1) Year
- (2) Month
 Jan. to Aug. ---A to H
 Sep.--- J
 Oct.--- K
 Nov.--- L
 Dec.--- M
- (3) Lot
- (4) Part Number Mark




Fig.3 Desirable land area (in mm)

Pin no.	Connection
1	GND
2	IN
3	GND
4	OUT

Notice

1. Use this component within operating temperature range. It might not be satisfied with electrical specification without operating temperature range. When it is used less than -40°C or more than $+105^{\circ}\text{C}$, it might be a cause of degradation or destruction of the component. Even if it endures during a short time, it causes degradation of qualification.
2. When soldering iron is used, solder with the temperature at the tip of soldering iron: 350°C maximum, the time of soldering: 5 seconds maximum, the power of soldering iron: 30 W maximum.
3. Notice that the allowed time of soldering with soldering iron is accumulated time, when soldering is repeated.
4. As rapid temperature change for cleaning after reflow soldering might be a cause of destruction clean this component after confirming that temperature of this component goes down to room temperature.
5. Confirm that there are not any influence for qualification to this component in mounting on PCB when this component is cleaned.
6. As it might be a cause of degradation or destruction to apply static electricity to this component, do not apply static electricity or excessive voltage while assembling and measuring. And do not transport this component with bare hand.
7. As it might be a cause of degradation or destruction to apply DC voltage between each terminal, apply DC voltage 7.5 V maximum in actual circuit.

Note

1. This specification specifies the quality of this component as a single unit. Make sure that this component is evaluated and confirmed against this specification when it is mounted to your products.
2. The information contained herein may be changed without prior notice. It is therefore advisable to contact New Japan Radio Company before proceeding with the design of equipment incorporating this product.
3. The products are designed to be used with ordinary electronic equipment (data and communications equipment, office equipment, audio-video equipment, measuring instruments, etc). New Japan Radio Company does not assume any liability for the case using the products with the application required high reliability or safety extremely (such as space equipment, sea-bottom equipment, medical equipment etc). When intending to use any our product please contact our sales representatives in advance.

